

#### TITLE CONCEALED ROD PADDLE HANDLE **PR-7085P SERIES EXIT DEVICE**

SHEET No.

4:10

SUB TITLE **TECHNICAL INFORMATION PR-7085P** 



### MOUNTING INSTRUCTIONS

- 1. Determine hand of door and prepare inside of lock and hinge stiles as show.
- 2. If Cylinder Key Lock is to be used, prepare inside and outside of lock stile as shown.
- 3. Insert Rod and Case Assembly into lock stile and secure with (2) 1/4-20 Shoulder Studs.
- 4. If Key Lock is used, insert Cylinder in Mounting Pad and secure with Locking Ring. Install using (2) #8-32x1-23.8mm Flat Head Machine Screws.
- 5. Position Exit Pad over stile and attach Actuator Link to Actuator Pin using Connecting Pin provided. Place on stile over 1/4-20 Shoulder Studs and tighten 3 Socket Head Set Screws to secure in place.
- 6. Adjust length of top and bottom Latch Bolts by turning in or out. When the Panic Arm is fully depressed, the Latch Bolts should be slightly recessed from flush with the top and bottom of the door. NOTE: Flat notch side of Bolt **must** face the outside of the door. Install top and bottom Latch Bolt Guides using (6) #10x12.7mm Flat Head Self-threading Screws.
- 7. Install (2) 1/4-20 Shoulder Studs on hinge stile. Place other Exit Pad over Studs and tighten 3 Socket Head Set Screws to secure in place.
- 8. Prepare header and threshold as shown. If Header and Threshold Strikes are required, install using (4) #8x9.5mm Flat Head Self-threading Screws or (4)#8x25.4mm Flat Head All-purpose screws.

DOGGING EXIT DEVICE USING DOGGING PIN:

Fully depress push paddle and hold, push up Dogging Pin with screwdriver and rotate  $90^\circ$  in either direction.

### TO RELEASE EXIT DEVICE:

Hold push paddle down and rotate Dogging Pin with screwdriver in either direction until Dogging Pin releases.

### DOGGING EXIT DEVICE USING CYLINDER KEY:

Fully depress push paddle and hold, turn Key clockwise approximately 60°, return Key to centre and remove.

#### TO RELEASE EXIT DEVICE:

Turn key counterclockwise 90°, return Key to centre and remove.



## The Parkside Group Ltd

The Willow Centre 17 Willow Lane, Mitcham, Surrey, CR4 4NX Tel: 020-8685 9685 Fax: 020-8646 5096 Email: axim@parksidegroup.co.uk Web Site: www.axim.co.uk

#### SCALE NTS @A4 DATE MARCH 2014

For scaled technical or CAD drawings, please contact AXIM.



## TITLE CONCEALED ROD PADDLE HANDLE PR-7085P SERIES EXIT DEVICE

## SUB TITLE FITTING GUIDE FOR DOGGING PIN DP-713



1) Remove securing screw in back of handle unit



2) Once securing screw is removed existing pin should be ejected by internal spring



3) Replace existing pin with knurled pin (retaining original spring)



4) Replace securing screw holding knurled pin in far enough that notch on dogging pin can locate on securing screw



## The Parkside Group Ltd

The Willow Centre 17 Willow Lane, Mitcham, Surrey, CR4 4NX Tel: 020-8685 9685 Fax: 020-8646 5096 Email: axim@parksidegroup.co.uk Web Site: www.axim.co.uk

SCALE	NTS @A4
DATE	MARCH 2014

For scaled technical or CAD drawings, please contact AXIM.





## The Parkside Group Ltd

The Willow Centre 17 Willow Lane, Mitcham, Surrey, CR4 4NX Tel: 020-8685 9685 Fax: 020-8646 5096 Email: axim@parksidegroup.co.uk Web Site: www.axim.co.uk SCALENTS @A4DATEJULY 2017

For scaled technical or CAD drawings, please contact AXIM.



## TITLE CONCEALED ROD PADDLE HANDLE PR-7085P SERIES EXIT DEVICE

## 4:13

# SUB TITLE KEY CONTROLLED OUTSIDE TRIM LOCKING HANDLE FOR PR7085, PR7085P & PR7100 EXIT DEVICES

## LH-725 Locking handle

Key Controlled Outside trim for use with PR7085, PR7085P, and PR7100 concealed rod Panic Devices.

Uses Axim screw in Mortice cylinder with MS type CAM.

Not handed. (Field reversible).

All Axim Panic Exit Hardware is supplied with comprehensive instructions and full size templates for ease of installation.

Handle rotation 45° anti-clockwise from centre. OR Handle rotation 45° clockwise from centre.

0

22

36,5



Email: axim@parksidegroup.co.uk Web Site: www.axim.co.uk For scaled technical or CAD drawings, please contact AXIM.



### TITLE CONCEALED ROD PADDLE HANDLE PR-7085P SERIES EXIT DEVICE

SHEET No.

#### SUB TITLE LOCKING HANDLES DETAILS AND DIMENSIONS

	Locking Handle	Pin Length	Door Stile
	LH-725	P = 6 mm	46mm
	LH-730	P = 9 mm	49mm
	LH-740	P = 14 mm	54mm
	LH-745	P = 27 mm	67mm
27	LH-760	P = 23 mm	64mm







0

PUSH

## The Parkside Group Ltd

The Willow Centre 17 Willow Lane, Mitcham, Surrey, CR4 4NX Tel: 020-8685 9685 Fax: 020-8646 5096 Email: axim@parksidegroup.co.uk Web Site: www.axim.co.uk

SCALE	NTS @A4
DATE	NOVEMBER 2019

For scaled technical or CAD drawings, please contact AXIM.